


Netgear Router Setup for Static IP Address



- Take the cable out of the existing computer and plug it into the WAN or Internet Port on the router.
- Take the cable that came with your router and plug it into the computer and one of the LAN ports (numbered) of the router.
- Turn off the computer.
- Unplug the DSL modem.
- Be sure to connect the network in the correct order. The computer, router and DSL modem should be off now.
- Turn the DSL modem on and wait at least 2 minutes
- Power up the router and wait at least 1 minute.
- Lastly, turn on your computer
- Connect to the router by typing <http://www.routerlogin.net> in the address field of your browser, then click Enter.
-



- When prompted for a username and password, use "admin" for the username and "password" for the password.

Internet IP Address

Get Dynamically From ISP

Use Static IP Address

IP Address 10 . 1 . 31 . 134

IP Subnet Mask 255 . 255 . 255 . 0

Gateway IP Address 10 . 1 . 31 . 13

Domain Name Server (DNS) Address

Get Automatically From ISP

Use These DNS Servers

Primary DNS 0 . 0 . 0 . 0

Secondary DNS

- Once logged into the router, you will choose Use Static IP Address.

- Enter the information provided to you at the time of installation. This information will be similar to the the table below.

IP Address:

Subnet Mask:

Gateway:

Primary DNS Server Address: 66.38.0.240

Secondary DNS Server Address: 66.38.1.240

- Click "Wireless Settings" to set up your security settings.

Wireless Settings

Wireless Network

Name (SSID):

Region:

Channel:

Mode:

Security Options

None

WEP

WPA-PSK [TKIP]

WPA2-PSK [AES]

WPA-PSK [TKIP] + WPA2-PSK [AES]

Security Encryption (WEP)

Authentication Type:

Encryption Strength:

Security Encryption (WEP) Key

Passphrase:

Key 1:

Key 2:

Key 3:

Key 4:

Do not operate your router without implementing wireless security. You may find out more about wireless network security by [clicking here](#). You may also consult your router documentation located on your router CD. NOTE: It is very important to use wireless security to avoid access to your network and someone hijacking your Internet connection. If someone uses your connection, you are responsible for their actions.